

ETP-LSM Line Seizure Module INSTALLATION INSTRUCTIONS

I. Getting Started

A. Introduction

The ETP-LSM allows a Talk-A-Phone Emergency Phone to share a phone line with a standard analog phone, while ensuring that the emergency call ALWAYS is the first priority. If the phone line is in use when an emergency call is placed, the ETP-LSM will seize the line and disconnect the non-emergency call so that the emergency call can go through. The LED lights to indicate that the emergency phone has seized the line. The ETP-LSM blocks the non-emergency line until the emergency call has been completed.

In the event of a power failure, the ETP-LSM gives the phone line exclusively to the Emergency Phone. This ensures the operation of the Emergency Phone. When the power is restored, normal operation automatically resumes.

Because the non-emergency phone receives all incoming calls, you must program the Emergency Phone before connecting it to the ETP-LSM.

B. What Is In The Box

- One 1 Model ETP-LSM Line Seizure Module
- One Power Supply
- One Instruction Manual

You should inspect your Line Seizure Module when you open the box for possible damage in shipment. If it is damaged, or any of the components are missing, contact your Talk-A-Phone Co. distributor immediately. Do not discard any hardware or packing material before you are certain you have all the items listed above, and the unit is installed and functioning correctly.

C. Technical Requirements

When connecting Emergency Phone to an ETP-LSM, we strongly recommend twisted, shielded pairs with the shield connected only at the ETP-LSM end. The resistance on the line is not to exceed 25 Ohms. The following chart shows distances and recommended wire gauges:

Distance from ETP-LSM to Emergency/Information Telephone	Recommended Wire Gauge
0 - 500 feet	24 G
501 - 750 feet	22 G
751 - 1,000 feet	20 G
1,001 - 1,800 feet	18 G
1,801 - 3,000 feet	16 G

Note: Model ETP-LSM Line Seizure Module may not be suitable for operation on all telephone company lines. Therefore it is important as part of installation to perform a complete operational test after installation is complete.

Talk-A-Phone Co.

5013 North Kedzie Avenue Chicago, Illinois 60625-4988
Phone: (773) 539-1100 Fax: (773) 539-1241
e-mail: info@talkaphone.com http://www.talkaphone.com

II. Hardware Installation

A. Connecting the Power Supply

The ETP-LSM has a power connector receptacle. The connector on the power supply plugs into this receptacle. The power supply itself plugs into a 110-120 volt, 50-60 Hz source of clean power.

B. Connecting Emergency Phones & Phone Line

Connect the Emergency Phone, and local analog phone to the ports marked appropriately. Then connect the phone company line or PBX extension to the port marked "TELCO IN".

III. Software Programming

The ETP-LSM unit does not require programming. To program the Emergency Phones, see the Emergency Phone Manual included with each of your Emergency Phones.

VIII. Talk-A-Phone Co. Limited Warranty

Talk-A-Phone Co. warrants Talk-A-Phone equipment against any defects in material and workmanship, under normal use, for a period of twelve (12) months from date of installation, provided that Talk-A-Phone receives a completed "Installation Certification" certifying the date on which the system has been installed. An "Installation Certification" card is enclosed with every unit. In the event that no "Installation Certification" is received by Talk-A-Phone, the twelve (12) months will commence on the date of shipment by Talk-A-Phone. The warranty period for Models ETP-PM, ETP-MT and ETP-MT/R is five (5) years, under the same terms and conditions.

In the event this product is found by Talk-A-Phone to be defective within the warranty period, Talk-A-Phone's only obligation and your exclusive remedy shall be the repair and/or replacement of any defective parts, provided the equipment is returned to Talk-A-Phone Co., 5013 N. Kedzie Ave., Chicago, IL 60625. It is expressly understood that Talk-A-Phone shall have no obligation to furnish labor, nor pay for the labor of any third parties, nor bear the expense of shipping defective products for repair. This warranty shall not apply if Talk-A-Phone determines that the defect was caused by improper use or installation, or damage caused to the equipment by others.

THIS WARRANTY GIVES YOU SPECIFIC LEGAL RIGHTS AND YOU MAY ALSO HAVE OTHER RIGHTS WHICH VARY FROM STATE TO STATE.