

AeGIS 4000

SINGLE LINE "NON SUBSCRIBER" TELEPHONE ACCESS CONTROL SYSTEMS



FEATURES

- **Hands Free Single Phone Line "Non Subscriber"** Telephone Entry Access System.
- Uses existing phone line or dedicated phone line (two systems can be installed).
- Optional Radio Receiver.
- **Programming** local via built-in keypad or remote via a touch tone phone.
- **Remote Access** press 9 to unlock door 1 or press 8 to unlock door 2 or optional Radio Transmitter
- **Local Access** keypad entry code (50 programmable codes).
- **Distinctive Ringing.**
- **Call Waiting.**
- **Automatic and Manual Call Forwarding** to call a secondary phone number.
- **Built Auxiliary Input** for radio frequency receiver, timer, free exit switch, panic bar, etc.
- **Recess Keypad w/ Built-in night light.**
- Brushed Stainless Steel Faceplate.
- Surface and full-flush Mount, outdoor or indoor.

SPECIFICATIONS

Power Input: 12VAC 40VA UL Listed Transformer (supplied) or 12VDC 40VA (output reading must be 13.5 - 14.5 VDC).

Current Consumption: 420 mA idle, 620 mA operating.

Emergency Battery: 12 VDC 4 Ahr rechargeable battery with 12 VDC charger (not supplied).

Operating Environment: 0°F to 140°F
Relative Humidity 0 % - 95 % noncondensing.

Relay: Two built in relays. Form C Dry Contact 120 VAC 10A, 24VDC 10A or 250VAC 7A. Programmable output 01-90 seconds.

Dialing: Touch-tone.

Memory Type: EEPROM (non-volatile).

Programmable Talk Time.

Standard Programming: Via built-in keypad and touch-tone Phone.

Construction: 16 Gauge Cold Rolled Steel back box with enamel finished and Brushed Stainless Steel Faceplate.

Dimensions :

Surface mount 9-1/8" (H) x 6-15/16"(W) x 3-7/8"(D).

Full-flush mount 9-11/16" (H) x 7" (W) x 3" (D)

Mounting Ring (included):

Inside 9-7/8" (H) x 7-1/4" (W) x 3-1/8" D)

Outside 13"(H) x 10-1/4"(W)

Shipping Weight: 8 Lbs. approximate.

"TWO YEARS WARRANTY" includes lightning and power

ORDER PART NUMBER

4000 (Brushed Stainless Steel Faceplate).

4000FF(Full-flush with brushed Stainless Steel faceplate, mounting ring is included).

FFM4 Spare full-flush mounting ring

OPTION AND ACCESSORIES

ARFR Radio Frequency Receiver

ARFT Radio Frequency Transmitter

ASP1 AC & Telephone Line Surge Protector.

APM1 Pedestal Mounting Post for auto and pedestrian.

APM2 Double arm mounting base plate for auto, pedestrian and semi-truck.

APM3 Pedestal mounting post for semi-truck.

APM4 Pedestal Mounting Post with 45° arm (protected environment only).

APM5 Double arm side by side mounting base plate.

AVP4 AeGIS Black and White Video Package.

AVP4C AeGIS Color Video Package.



Pach & Company
www.pach-co.com

941 Calle Negocio
San Clemente, CA 92673

Phone: 1-888-678-7224
Fax: 949-498-6879